

1. Sensitivity

Sensitivity can be adjusted by selecting the combination on the DIP switches for different applications.

- I – 100%
- II – 50%

	1	
I	●	100%
II	○	50%

2. Hold-time

Hold-time refers to the time period that the light remains 100% on if no more movement is detected.

- I – 5s
- II – 90s
- III – 180s
- IV – 10min

	2	3	
I	●	●	5s
II	●	○	90s
III	○	●	180s
IV	○	○	10min

3. Daylight threshold

Different daylight threshold can be preset on DIP switches. Light will always turn on upon movement if daylight sensor is disabled.

- I – Disable
- II – 10Lux

	4	
I	●	Disable
II	○	10Lux

4. Stand-by time

This is the time period that the light remains at a low level before it is completely turned off.

- I – 0s
- II – 10s
- III – 10min
- IV – +∞

	5	6	
I	●	●	0s
II	●	○	10s
III	○	●	10min
IV	○	○	+∞

5. Stand-by dimming level

Light can be dimmed to different levels after hold-time.

- I – 10%
- II – 30%

	7	
I	●	10%
II	○	30%