LTECH

FC CE RoHS




warranty 5 years

# 2 4G LED Color Temperature Controller

# **Main Characteristics**

## V6 RF CT Remote Control

Remote Option:	CT, 4 Zones control		
Working Voltage:	3Vdc (Battery CR2032)		
Wireless Frequency:	2.4GHz		
Working Temperature:	-30 ~55		
Package Size:	L150×W46×H18(mm)		
Weight(G.W.):	85g		



### R4-5A CV Receiver

Input Voltage:	5~24Vdc
Max Current Load:	5A × 4CH Max. 20A
Max Output Power:	100W/240W/480W(5V/12V/24V)
Working Temperature:	-30 ~55
Package Size:	L178×W48×H33(mm)
Weight(G.W.):	150g


#### R4-CC CC Receiver


Input Voltage:	12~48Vdc
Output Voltage:	3~46Vdc
Output Current:	CC 350/700/1050mA×4CH
Output Power:	1.05W~48.3W×4CH Max 193.2W
Working Temperature:	-30 ~55
Package Size:	L178×W48×H33(mm)
Weight(G.W.):	165g




#### Dimensions

Unit: mm










R4-5A/R4-CC



R4-5A/R4-CC

## **Operating Instruction for Remote:**





## **Operating Instruction for Receiver:**


The running light		
ID learning button		LED lamp
5~24Vdc CV power supply	R4-5A	

The running light

ID learning button		LED lamp
12~48Vdc CV power supply	R4-CC	connection
Current selection switch	ON ON ON	
Operation table 350mA 70	0mA 1050mA	


## Wiring Diagram:





## Match/Clear code between remotes

#### Match code:




1. Short press the ID learning button on the receiver, the running light keeps on.



2. Press the matching zone key "ON" or "OFF on the remote, the running light on the receiver flicker several times, match successfully

#### Clear code:

Receiver Long press "ID learning button" on receiver for Ē . 5 seconds, If the running light flicker several times, deactivate the matching successfully. ID learning button



### Attention:

- · Please replace the battery if the remote becomes insensitive or control distance is shortened.
- · Please take out the battery for long time unused.

...